

Good and Practical 150 GPD RO Hook Up For a Primitive Environment using a 12V Pump.

Ceramic filters are a good second choice to RO for after PS when Gravity is all you can use for cleaning up water.

2011, John wrote:

I am in the process of putting together a 150 GPD RO unit that would use the Aquatec 8800 RO Boost Pump. I noticed on this page

<http://www.rvwaterfilterstore.com/Pumps.htm> that you indicate dual membranes can be hooked up in series. I am very interested in how this would work.

I have all of the sediment and water softening filters and carbon filtration up-stream from the RO filter where it empties into an at atmospheric pressure holding tank. This is a homemade out in the country unit that uses local rain runoff water. I would be using the 8800 pump between two open air holding tanks (one input and one output) and would plan to have the pump below the surface level outside the tank. This would be so it remains primed when turned off. I am thinking a pressure gauge would be needed at the input of the two series connected RO filters. I believe the optimum pressure across each membrane would be 60 to 65 PSI. The input pressure bypass on the pump would be adjusted to the pressure across each filter. I am not sure how high this two series ro membranes would boost the input pressure. It is one of my questions. I am thinking the second series filter would always have less pressure on it due to less flow or does one use a 100 GPD filter for the second one that is in series? A way of fast flushing both would be needed. Thinking of using Flow Restrictor - flush to waste kit might work on both.

I plan to use UltraTec TF Membrane TF-1812-150. Assuming under ideal conditions 98% rejection for both membranes in series I doubt that anything approaching the theoretical product of the two $.02 * .02 = .0004$ (99.96%) would be attained. But the question arises is what would be the rough order result? In other words is it worth while doing?

The basic questions I have are --- What are your comments? Is this thinking on the right track let me know what will and will not work? What other items are needed or desired to make this work?

If one uses Ozone or UV light to kill pathogens before it reaches the membrane --- is there any problems using it up front before all pre-filters?

John

John,

We hook up dual membranes in series all the time. We always match them to be the same size. The waste from #1 membrane feeds the #2 membrane and it leaves only one waste. The pressure stays up about 85 psi with the 8800 boost pump. The whole point is to cut the waste water in half as to ratio of product to waste. An auto-flush unit is great for any

membrane or dual membrane setup, although not necessary. They are for the intended goal of longer life by creating a periodic super flush. I am sure there are some aspects of this that could result in hydronic studies and engineering tests being done to figure out exactly what is happening. We don't do that. We just know it works pretty well and rejection is good and production to waste ratio winds up being about 1 1/2 or 2 to 1, versus the 3 to 1 we try to set up ours to. It sounds like you are taking cistern water and running it through the RO and storing it in another non-pressurized tank. I only see a pressure switch being used if you plan to store the water in a pressure tank, because this is where the pressure needs to be sensed. If no pressure storage tank is used, then a float switch with a TLC (tank level controller) will turn the pump on and off if installed in a non-pressurized tank. As to the value of an RO unit with this kind of system, I have some doubt. You are dealing with mineral free rain water and that is the biggest value over good filtration the RO will have. So I wonder why you would not just use a delivery pump taking the water from the cistern and pumping it through ceramic and carbon filtration or UV or ozone and that be the end of it. What is it that makes you need the RO? You can put UV or ozone ahead of the RO, or after it, if that is what you decide to do.

Richard

2011, John wrote:

Your practical experience-knowledge is very much appreciated.... I need to tap into a bit more of it.

I can see I had the idea of the in-series hook up all wrong. I had the output of the one filter going into the input of the next filter. It makes much more sense the way you described it. I take it with the waste feeding the number 2 membrane that a restrictor is not needed until at the point the waste of number 2 exists number 2 membrane?

So I take it you set the bypass on the 8800 to about 85 PSI or do you set it a bit higher and it will settle in and run at about 85 psi?

I agree with you and already have a float type tilt sw that will turn the pump off when the output tank is full or the input tank is empty.

Your point is well taken for rain water most of the time being low in dissolved solids.

You mentioned ceramic filter --- Can you indicate a reference to what you were thinking about?

I am currently familiar with down to .5 micron carbon filters and plan to use them.

I have heard one should not use ozone before a carbon filter for it will heat up and eat up the carbon when it gets to it. Is this correct?

I have also heard that one can remove ozone from water by letting it sit in an open container for a while or by passing it past a UV light water filter. Would either of these work to remove the ozone from water before sending it through a carbon filter? Or is this totally un-necessary?

John,

Yes, only one restrictor on #2 membrane. We don't mess with setting the bypass at all. They come set and the 8800 will produce about 85 psi on the membranes. We carry English made Doulton ceramic filters. They have been around over a hundred years and are very practical, in that they are made to be cleaned and reused. We have the Imperial Sterasyl that we call the D-ST, that flows about a maximum of 2 gpm at 60 psi, or the Doulton RIO 2000 that fits a jumbo canister and flows about 5 gpm at 60 psi. These are rated for all bacteria. I have not heard of a carbon issue about ozone, but then I don't carry ozone and have not gotten into any extensive info on their operation other than how they produce the ozone. Ozone will dissipate very quickly by leaving it open to the air. In dealing with RVers that are often short on space and not into too much redundancy, we try to specialize in simpler products that perform specific tasks. UV with filtration is one choice, as is ozone with filtration. RO is a whole different approach to a number of issues. But chemicals, pesticides, cysts, taste and odor from various gasses, sediment, even all bacteria is more of a higher end filtration job, not necessarily a more elaborate system when dealing with rain water. I will leave you a couple of links to see what the ceramic is about, and the equipment to house them.

<http://www.rvwaterfilterstore.com/RCSpecialtyCartridge.htm>

Doulton RIO 2000

<http://www.rvwaterfilterstore.com/WCJumboCanisters.htm>

<http://www.rvwaterfilterstore.com/WCStandardCanisters.htm>

Richard

On 2011, John wrote:

Thank you again for the wealth of info.

Just one question remaining -- How do you clean the Ceramic and Carbon Block filters?

John,

The carbon filters are not cleanable except for the KX Ceramix, which is not a ceramic filter, but a very smooth carbon block, made to be cleaned, but with a very slow flow rate for drinking water only. The Doulton ceramic cartridges are certainly cleanable and it is done with a vegetable brush or the rough side of a scotch-brite sponge. You start at the top and scrape down and turn the filter until you have rubbed the whole surface of the cartridge. You are not trying to rub it hard and repeatedly, nor do you want to add anything, such as soap or bleach, etc.

Richard.



-- Take apart and use the individual candles or use as is in gravity feed plastic 5 gallon bucket as described below.

Dear John,

These ceramic candle filters need no power or pressure to work. Although they can accept pressure they can operate with just gravity. Here is how they work with buckets. In an emergency situation is where these filters are at there best. They can filter water from lakes, ponds, floods, streams or stagnate pools of water turning into clean safe drinking water. You will swear that you are drinking bottled water. You take one bucket and drill a 3/8" hole in the bottom. One for each filter you are going to use. Then you take one bucket lid and drill holes to match the ones you drilled in the bucket. The filter stem will go though the bucket, through one of the gaskets that come with the filter, then through the lid. Everything is fastened together with a nut that also comes with the filter. Once this bucket setup is made then you take a second bucket and install a water spigot at the bottom side of the bucket. The first bucket, with the filters, sets on top of the second bucket. Fill the top bucket with water. After a while you will be able to drink the water from the bottom bucket. We have the spigots at our Ebay store.

The more filters you use the more water you will get. Each filter produces about 5-7 gallons of drinking water a day.

Food grade buckets are available at bakeries or restaurants. They are usually free to anyone who wants them. Lids can be purchased at Lowes, Home Depot or Ace Hardware for about \$1.

I hope that this answers your question.



A large 10 inch have duty housing can be purchased at home Depot or Lows or on line at ebay.com.

Next order a "Doulton W9120145 Rio 2000 Candle Replacement Filter for about \$125.



This will fit the above Cartridge Housing. Gravity or a pump between two holding containers is all that is needed to complete the filter.

The following is a smaller filter but just as effective.

Doulton W9220406 **Imperial Sterasyl** Ceramic Filter Specs: Dimensions: 9.75" (248 mm) long X 2.75" (72 mm) Diameter Micron



Typical data on good ceramic filters are as follows.

- Doulton W9220402 Sterasyl OBE Ceramic Filter:
- The Doulton W9220402 Sterasyl Ceramic Filter is a **self-sterilizing** filter that can be re-used over and over again to provide absolute micron filtration down to .9 microns, at an economical price.
- The Doulton W9220402 cartridge is open on both ends (OBE) and fits in standard 10" filter housings.
- The Doulton W9220402 Hollow Core OBE Filter features a Sterasyl ceramic outer shell with no core.
- The Doulton Slimline Sterasyl ceramic shell is **silver impregnated ceramic**. The incorporation of silver locked within the ceramic structure inhibits the growth of bacteria and gives each cartridge enhanced bacteriostatic and self-sterilizing properties.
- Doulton Sterasyl Ceramic Filter W9220402 is ideal for RO guard and post filtration and complimentary to UV systems.
- The Doulton Sterasyl W9220402 Ceramic Filter is **NSF Certified** for Standards 42 & 53.
- Doulton W9220402 Imperial Sterasyl Ceramic Water Filter Contaminant Reduction:
 - **Absolute filtration rating (defined as > 99.99%):** 0.9 micron
 - **Nominal filtration rating (defined as > 99.9%):** 0.5 - 0.8 micron
 - **E.coli Bacteria:** > 99.99% removal
 - **Vibrio Cholera Bacteria:** > 99.99% removal

- **Shigella Bacteria:** > 99.99% removal
- **Salmonella Typhi Bacteria:** > 99.99% removal
- **Klebsiella Terrigena Bacteria:** > 99.99% removal
- **Cryptosporidium:** > 99.99% Cyst removal
- **Giardia:** > 99.99% Cyst removal
- Doulton W9220402 Sterasyl Ceramic Filter Specs:
- **Dimensions:** 9.75" (248 mm) long X 2" Diameter
- **Micron Rating:** 0.9 micron
- **Working temperature range:** 41°F (5°C) - 100°F (38°C)
- **Working pH range:** 5.5 - 9.5 F
- **Certifications:** NSF 42, NSF 53
- **Minimum working pressure:** 10 psi
- **Maximum working pressure:** 125 psi
- **Flow rate:** 1.33 gpm
- **Recommended cleaning frequency:** when flow rate is noticeably lower
- **Capacity:** 2600 gallons
- Doulton W9220402 Sterasyl Ceramic Filter:
- Doulton W9220402 OBE water filter fits in standard 10" filter housings.
- Doulton W9220402 Sterasyl Ceramic Filter Maintenance:
- The ceramic shell of the water filter is designed to filter fine particles, bacteria and other contaminants from your water. In doing so, the outside of the ceramic shell can eventually need cleaning which will become evident when water flow from the filter becomes reduced. When this occurs, simply **remove, clean and replace** the cartridge as follows:
- **1st:** Wash your hands with filtered water.
- **2nd:** Remove the ceramic cartridge according to the instructions of your particular filter housing (Handle with care. Wet cartridges are fragile!)
- **3rd:** Take a clean scouring pad, or slightly abrasive cloth, and give the ceramic a light scrub under running water. Apply gentle pressure uniformly, take care that the cleaning of the ceramic is not concentrated in one area. This will remove surface particles from the water filter as well as an outer layer of ceramic, restoring and refreshing the water filter to it's original water flow.
- **4th:** Replace cartridge in filter housing.
- **5th:** Wash hands thoroughly after handling the ceramic cartridge.
- Cleaning can be done over 50 times before replacement of the water filter cartridge will be necessary.